



RELIABILITY Power Systems

REL2931II 6 ~ 20KVA

True Online Dual Conversion UPS System

www.reliability-power.com

REL2931II

6KVA ~ 20KVA (3:1)
PF 0.9



Features

- High frequency and true double-conversion
- DSP digital control technology
- Wide input voltage range (110V ~ 300V)
- Output power factor 0.9
- Optimized battery configuration: 192V / 240V
- Cold start
- Auto sensing frequency
- ECO mode operation for energy saving
- 50/60Hz frequency conversion mode
- Selectable output voltage via LCD
- Selectable battery shutdown voltage (EOD) via LCD
- Selectable input mode via LCD (3:1 or 1:1)
- Power-on self test
- Advanced battery management (ABM)
- Short circuit and overload protection
- Automatic charging in OFF mode
- Fan speed auto control when temperature varies
- Standard RS232 / USB communication port
- Standard emergency power off (EPO)
- Optional RS485 / SNMP / AS400 communication port
- Optional extension battery bank
- Optional battery temperature compensation
- Optional built-in isolation transformer
- Optional manual bypass
- Optional N+X redundancy parallel

Rear Panel

- | | |
|-------------|------------------------------|
| 1. AC Input | 7. EPO |
| 2. DC Input | 8. Manual Bypass (optional) |
| 3. Outlet | 9. SNMP/AS400 (optional) |
| 4. Fan | 10. Breaker |
| 5. RS232 | 11. Parallel Card (optional) |
| 6. USB | 12. BAT_NTC (optional) |



6/10KS

15/20KH

6/10KH

Specifications

MODEL		REL2931II			
Capacity		6 KVA / 5.4 KW	10 KVA / 9 KW	15 KVA / 13.5 KW	20 KVA / 18 KW
INPUT					
Rated voltage		3:1: 360 V / 380 V / 400 V / 415 Vac; 1:1: 208 V / 220 V / 230 V / 240 Vac (settable via LCD)			
Voltage range		3:1: half load (190 ~ 520) ± 5Vac, full load (277 ~ 520) ± 5 Vac; 1:1: half load (110 ~ 300) ± 5Vac, full load (160 ~ 300) ± 5 Vac.			
Frequency		40 ~ 70 Hz (auto-sense)			
Power factor		3:1 ≥ 0.95; 1:1 ≥ 0.99			
BYPASS					
Voltage range		160 V ~ rated output voltage +32 V			
Frequency		50 / 60 Hz ± 5 Hz			
OUTPUT					
Voltage		208 V / 220 V / 230 V / 240 Vac (settable via LCD)			
Voltage regulation		± 1%			
Frequency		Synchronized with utility in mains mode; 50 / 60 ± 0.2 Hz in battery mode			
Waveform		Sinusoidal			
Crest factor		3:1			
Harmonic distortion		≤ 2% (linear load); ≤ 5% (non-linear load)			
Transfer time		0 ms			
Overload capability		105% ~ 125%: transfer to bypass in 3 mins; 125% ~ 150%: transfer to bypass in 30 s; > 150%: transfer to bypass in 1 s			
EFFICIENCY					
Mains mode		≥ 92%			
Battery mode		≥ 91%			
ECO mode		≥ 98%			
BATTERIES					
DC voltage		192 Vdc / 240 Vdc			
Inbuilt battery of standard model		16 / 20 × 7 Ah	16 / 20 × 9 Ah	/	
Charging current	Standard model	1 A		/	
	Long time model	7 A			
Recharge time		8 h			
ALARMS					
Utility failure		4 s per beep			
Low battery		1 s per beep			
Overload		1 s twice beep			
UPS fault		Long beep			
COMMUNICATIONS					
RS232 / USB (standard)		Supports Windows® 98 / 2000 / 2003 / XP / Vista / 2008 / Windows® 7 / 8 / 10			
SNMP (optional)		Power management from SNMP manager and web browser			
OTHERS					
Humidity		20 ~ 90% RH @ 0 ~ 40°C (non-condensing)			
Noise level		≤ 58 dB (1m)		≤ 60 dB (1m)	
Dimensions (W × D × H) (mm)		262 × 580 × 455 (H), 262 × 580 × 732 (S)		262 × 580 × 628 (H)	
Packaged dimensions (W × D × H) (mm)		355 × 682 × 615 (H), 359 × 687 × 937 (S)		359 × 687 × 832 (H)	
Net weight (kg)		25.0 (H), 73.0 (S)	25.5 (H), 74.0 (S)	38.5 (H)	39.0 (H)
Gross weight (kg)		28.5 (H), 82.5 (S)	29.0 (H), 83.5 (S)	47.0 (H)	47.5 (H)

- Derate capacity to 70% in CUCF mode and to 90% when the output voltage is adjusted to 208Vac.
- 3 : 1 means three-phase input and single-phase output mode; 1 : 1 means single-phase input and single-phase output mode.
- S means standard model, H means long time model.

- All specifications subject to change without notice.
- Custom-made specifications are acceptable.

Reliability Power Systems Australia

Level 17, 40 Mount St. North Sydney
NSW 2060, Australia
reliability@reliability-power.com

Reliability Power Systems

Reliability Power Systems Canada

4th Floor 2 County Blvd, Brampton
ON L6W 3W8, Canada
reliability.ca@reliability-power.com

Reliability Power Systems Europe

New Summer St, Birmingham
West Midlands B19, UK
reliability.eu@reliability-power.com

Reliability Power Systems Asia Pacific

5/F China Life Tower, No.16 Chaowai St.
Chaoyang Dist, Beijing 100020, China
reliability.cn@reliability-power.com